

# MASCALI SQUARE 7968

SKU 1373003

astro



## PRODUCT SPECIFICATION

### GENERAL

<b>FINISH:</b>	Polished Chrome	<b>CABLE LENGTH:</b>	Not Applicable
<b>MAIN MATERIAL:</b>	Metal - Mild Steel	<b>GROSS WEIGHT:</b>	1.93 (Kg)
<b>DIMENSIONS:</b>	H: 214mm W: 214mm D: 284mm	<b>CLASS:</b>	CE (Class II)
<b>INSTALLATION ORIENTATION:</b>	Wall Mount - Horizontal	<b>IP RATING:</b>	IP44
<b>CUT OUT HOLE:</b>	Not Applicable	<b>BATHROOM ZONE:</b>	Zone 2, 3
<b>RECESS DEPTH:</b>	Not Applicable	<b>VOLTAGE:</b>	Mains 230V
<b>FIRE RATING:</b>	Not Applicable	<b>PRODUCT F MARK:</b>	Suitable for mounting on flammable materials

### LAMP

<b>LIGHT SOURCE:</b>	LED Strip	<b>MACADAM ELLIPSE:</b>	5-Step
<b>MAXIMUM WATTAGE:</b>	6.1W	<b>UGR:</b>	Not Applicable
<b>MAXIMUM LAMP LENGTH:</b>	Not Applicable	<b>BEAM ANGLE:</b>	Not Applicable
<b>LAMP INCLUDED?</b>	Yes (Integral)	<b>TILT ADJUSTMENT ANGLE:</b>	65 (Degrees)
<b>LUMINOUS FLUX:</b>	152.6 (lm)	<b>ROTATION ADJUSTMENT ANGLE:</b>	180 (Degrees)
<b>COLOUR TEMP:</b>	2700 (K)	<b>AVERAGE LIFESPAN:</b>	Not Applicable
<b>CRI:</b>	80	<b>L70:</b>	To Be Advised
<b>R9:</b>	-9.0		

### ELECTRICAL

<b>SWITCHED:</b>	Yes	<b>SUPPLY FREQUENCY:</b>	50/60 (Hz)
<b>DIMMABLE:</b>	No	<b>DRIVER/BALLAST VOLTAGE:</b>	100-240 (V)
<b>DIMMING METHOD:</b>	Not Applicable	<b>DRIVER AVERAGE LIFESPAN:</b>	35,000 (Hrs)
<b>DRIVER OUTPUT CURRENT:</b>	Not Applicable	<b>EFFICACY:</b>	25.02 (lm/W)
<b>DRIVER OUTPUT VOLTAGE:</b>	12 (V)	<b>DRIVER/BALLAST INCLUDED?</b>	Yes (Integral)

## ADDITIONAL INFORMATION

CE



BOX QUANTITY x 6

## PRODUCT ELEVATIONS

**GB** Please note that some dimensions may vary slightly due to manufacturing tolerances, this includes cable entry and fixing holes.

**FR** Veuillez noter que certaines dimensions peuvent varier légèrement en raison des tolérances de fabrication, y compris l'entrée de câble et les trous de fixation.

**DE** Bitte beachten Sie, dass die Maße Fertigungstoleranzen unterliegen und daher in geringem Umfang von der angegebenen Größe abweichen können. Dies gilt auch für Kabeleingänge und Befestigungslöcher.

**IT** Si prega notare che possono esserci piccole variazioni in alcune dimensioni dovute alle tolleranze di produzione, queste includono l'ingresso del cavo e i fori di fissaggio.

